LBP6030w 安裝 Mac 透過 USB 連線連接印表機之驅動程式步驟

注意:安裝驅動程式前請勿接駁 USB 線,以免系統發生錯誤

- 到佳能網站 <u>https://hk.canon/en/support/0100934901/11</u> ,下載印表機的驅動程式 (Go to: <u>https://hk.canon/en/support/0100934901/11</u>, then download the printer driver)
- 2. 開啟下載檔案「UFRII LT Printer Driver 」,進入「SFP」文件夾(Open "UFRII LT Printer Driver", then open "SFP")



3. 開啓"UFRII_LT_***.pkg"文件開始安裝設定 (Double Click / Open "UFRII_LT_***.pkg")



4. 按「Continue」(Choose "Continue")



5. 按「Continue」(Choose "Continue")



6. 如出現以下畫面,按「Agree」 (Choose "Agree")

	the software lie	cense agreement.	
 Intr 	Click Agree to continue or click Disagree to cancel the installation and		
• Lic	quit the Installer	r.	
 De: 			
Ins	Read License	Disagree Agree hu	
Ins			
Summ	hary	READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AN RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLIN	
Summ	hary	READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AN RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLIN THE SOFTWARE. BY CLICKING THE BUTTON INDICATING YOU ACCEPTANCE AS STATED BELOW OR INSTALLING THE SOFTWARE, YO AGREE TO BE BOUND BY THE TERMS AND CONDITIONS OF TH AGREEMENT. IF YOU DO NOT AGREE TO THE FOLLOWING TERMS AN CONDITIONS OF THIS AGREEMENT, DO NOT USE THE SOFTWARE.	

7. 按「Install」 (Choose "Install")



8. 如出現以下畫面,請輸入登入密碼 (Type your password)

Installer is trying to install new software. Type your password to allow this.		
Username:	Call Center	
Password:		
	Cancel Install Software	

9. 按「Close」 (Choose "Close")



- 完成安裝驅動程式後需新增印表機,到「系統偏好設定(System Preference)」, 選「印表機與掃描器(Printers & Scanners)」 (Go to "System Preference", then open "Printers & Scanners")
 - ● < > Ⅲ Q Search 8 System Preferences Q -۲ 0 0100 Mission Security Spotlight Notifications General Desktop & Dock Language & Region Screen Saver Control & Privacy 0 17 CDs & DVDs Displays Energy Keyboard Mouse Trackpad Printers & Sound Saver Scanners @ ∦ ∢ $\Delta \mathfrak{I}$ iCloud Internet Extensions Network Bluetooth Sharing Accounts $\Delta_{\rm c}$ 1 Ų X **JU** 18 Users & Parental App Store Dictation Date & Time Startup Accessibility Time Groups Controls & Speech Disk Machine Ś 14 Flash Player Java
- **11.** 選取左下角「+」按鈕,選「加入印表機或掃描器(Add Printer or Scanner)」 (Click "+", then choose "Add Printer or Scanner")

rinters	the second	192.168.1.105	
192.168.1.105		Onen Print Oue	
Canon LBP6680/348 • Offline Canon MF6100 Series		Options & Suppli	ies
Idle Canon MF6100 Series 2 Idle Canon MG3500 serie Idle	Location: Kind: Status:	Canon LBP6680/3480	l.
Canon MG7500 series • Offline Canon MG7500 series 2			
Offline Canon MX390 series	Share this printe	er on the network	Sharing Preferences
Add Printer or Scanner	Default printer:	Last Printer Llead	
Nearby Printers	Delaut printer.	Last i miter Osed	
Canon LBP6030w/6018w	Default paper size:	A4	<u></u>

12. 名稱選擇「Canon LBP6030***」,種類「Bonjour」,確認「使用(Use)」為「Canon LBP6030***」,然後按「加入(Add)」

("Name" chooses "Canon LBP6030***", "Kind" chooses "Bonjour". After you confirm "Use" is "Canon LBP6030***", then choose "Add")

		oouron		
Name		∧ Kind		
Canon LBP60	30/6040/6018L	USB		
Canon LBP60	30w/6018w	Bonjour		
Canon MF220		Bonjour Multifunction		
Name:	Canon LBP6030/6040/6018L			
Name: Location:	Canon LBP6030/6040/6018L Call Center's MacBook Pro			
Name: Location:	Canon LBP6030/6040/6018L Call Center's MacBook Pro			
Name: Location: Use:	Canon LBP6030/6040/6018L Call Center's MacBook Pro Canon LBP6030/6040/6018L			
Name: Location: Use:	Canon LBP6030/6040/6018L Call Center's MacBook Pro Canon LBP6030/6040/6018L	 		
Name: Location: Use:	Canon LBP6030/6040/6018L Call Center's MacBook Pro Canon LBP6030/6040/6018L			

- *** 如「使用(Use)」部份不是「Canon LBP6030***」,請按以下步驟設定*** (*** If "Use" is not "Canon LBP6030***", please reference the steps below***)
- a) 請如下圖打開「使用(Use)」的選單,選 Select Software (Open "Use", then choose "Select Software")

	Add
🔒 🌏 🚔	Q Search
Default IP Windows	Search
Name	^ Kind
Canon LBP6030/6040/6018L	USB
Canon LBP6030w/6018w	Bonjour
Canon MF220	Bonjour Multifunction
Name: Canon LBP6030)/6040/6018L
Location: Call Center's Ma	acBook Pro
Use ✓ Choose a Drive	r
Auto Select	
Select Software	a
Other	

b) 輸入 6030 以搜尋「Canon LBP6030***」 (type "6030", then choose "Canon LBP6030***")

		୍ ଦ୍ର 6030	8
Canon LBP6030/6	040/6018L		
_			
_			
		Cancel	ОК
		Cancer	UN
	_		_

13. 加入完成 (Finish)

Printers		
192.168.1.105 • Idle Canon LBP6030/604 • Idle, Last Used Canon LBP6030w/60 • Idle Canon LBP6680/348 • Offline Canon MF6100 Series • Idle Canon MF6100 Series 2 • Idle	Canon LBP6030/6040/6018L Open Print Queue Options & Supplies Location: Call Center's MacBook Pro Kind: Canon LBP6030/6040/6018L Status: Idle	
Canon MG3500 serie Idle Canon MG7500 series + -	Share this printer on the network Sharing Preference	es
	Default printer: Last Printer Used)
	Default paper size: A4	(