#### MX477 在 MAC OSX 透過無線 LAN 連線連接印表機之驅動程式步驟

請先將打印機連接到路由器,詳細可參考以下步驟:

# 無線網絡設定速覽

Step 1) 連接打印機至無線網絡路由器



按鍵盤上的"設定"鍵並選擇"設備設定"及"LAN設定"



按"停止"鍵進入無線網路設定介面



選擇需連線無線路由器的名稱

## 到以下網頁下載驅動程式:

https://hk.canon/zh\_HK/support/0100574601/7

1. 開啟 mac-mx470-1\_1-mcd.dmg 後按 Setup





按方向鍵選擇"無線LAN設定",然後按"OK"



選擇"標準設定",再按"OK"



利用鍵盤根據指示輸入密碼

#### 2. 按「Next」





4. 按「Wireless Connection」



1-2 Preparatio	for Connection			
	:====:	0		
Before Sta 1. Make sur	ting Wireless Conr e that the printer is t	nection Setup		
If the pov Click "Next"	ver is on, the (green) to proceed to the ne	) ON button (A) wil ext step.	l be lit.	
If the pov Click "Next"	ver is on, the (green) to proceed to the ne	) <b>ON</b> button (A) wil ext step.	l be lit.	
If the pov Click "Next"	ver is on, the (green) to proceed to the ne	) ON button (A) wil ext step.	l be lit.	
If the pov Click "Next"	ver is on, the (green) to proceed to the ne	) ON button (A) wil	l be lit.	

6. 按「Connect to the network」

Click here for notes on wireles	s connection	
Start setup	Connect to the network	

2-2 Printer Se	Dopy 100% Letter	01		
<u>کر چ</u> کا	:	⊞°°.		
1 Press th	e Setup button (A	A) on the printer.		
1.110334	e oetap batton (r	,,		
1.11033.0	o octup outon (r	,,		
1.110300				

# 8. 按「Next」

	Ganon : Pixinki manuais ; mx4ru series ; Secup Gi	
2-3 Printer Setup Setup menu Wireless LAN set		
A 1. Use the ◀ or 2. Press the OK The (blue) Wi-Fi connection is en	<ul> <li>button (A) to select Wireless LAN setup.</li> <li>button (B).</li> <li>lamp (C) lights up when wireless habled.</li> </ul>	
Start Again	Back Next	5

9. 按「Other Methods」

Iick the method below that matches the screen displayed on our printer.         Press MPS button of the       Wireless LAN setup Standard setup •         Push Button Method       Other Methods         If the Push Button Method       "WPS" or "Cableless setup" can be selected in the next step. If your access point supports         If your access point or router supports       Wireless LAN setup •	he printer will automatically points.	search for compatible access	
Press MPS button of the     Wireless L/N setup Standard setup       Push Button Method     Other Methods       If the Push Button Method     "WPS" or "Cableless setup" can be selected in the next step.       printer but you are unsure if your access point or router supports     Wireless L/N setup •	lick the method below that rour printer.	matches the screen displayed on	
Push Button Method         Other Methods           If the Push Button Method         "WPS" or "Cableless setup" can screen is displayed on the be selected in the next step.           printer but you are unsure if your access point supports access point or router supports         "WPS"	Press MPS button of the	Wineless LAN setup Standard setup	
If the Push Button Method "WPS" or "Cableless setup" can screen is displayed on the be selected in the next step. printer but you are unsure if your if your access point supports access point or router supports WPS	Push Button Method	Other Methods	
this technology, press the Stop button. setup screen is displayed. When the printer screen changes from left to right, click here.	If the Push Button Method screen is displayed on the printer but you are unsure if your access point or router supports this technology, press the <b>Stop</b> button. When the printer screen changes from left to right, click <u>here</u> .	"WPS" or "Cableless setup" can be selected in the next step. If your access point supports WPS, you can perform WPS setup, even if the <b>Wireless LAN</b> setup screen is displayed.	

# 10. 按「Other Setup」

Connect to WPS-compatib Point	le Access	WPS		
Setting the Access Point In to the Printer Directly from without Operating the Acce	formation Computer, iss Point	Cableless setup		
Cableless setup may take some unavailable during setup.	time. Internet connecti	on may become temporarily		
Connect Using Other Meth	ods	Other setup		

11. 按「Wireless Setup Using the USB Cable」

following.	ection method from the	
Wireless Setup Using a USB Cable Temporarily	Wireless Setup Using the USB Cable	
After software installation, the procedure to or Click "Wireless Setup Using the USB Cable,"	ennect your computer with the printer appears. then wait until the next screen appears.	

#### 12. 選擇居住地按「Next」





[Ne) You	selected software will be installed. Make s rt]. need to install all the software below to u	ure that the software you war se all functions of this printer	nt to install is selected, and then clic
~	MP Drivers	130 MB	Drive Macintosh HD 459205 MB free
1	IJ Scan Utility2	40 MB	space
-	User's Manual	100 MB	
-	My Image Garden	680 MB	
2	Quick Menu	25 MB	Total used space: 995 MB
2	Canon IJ Network Tool	20 MB	
			Select All

## 14. 按「Yes」



### 15. 可自訂是否在桌面放置說明書

License Agreement	Create an Alias on Desktop
STEP 2 Installation	Do you agree to create alias of manual on desktop? If you agree, select "Agree". If you select "Do not agree", you can open the manual from Applications Folder.
Create an Alias on Desktop MP Drivers User's Manual Applications	
STEP 3 Setup	Agree
STEP 4	
Information	O Do not agree
Back	Next

16. 等待安裝完成

• •	Setup
PIXMA	MX470 series
<b>G</b> )-	Installation progress: 0%
	Downloading MP Drivers
	Cancel

#### 17. 選擇「Add Printer」

	Setup
STEP 1 License Agreement STEP 2 Installation STEP 3 Setup	Add Printer When you click [Add Printer], printers that can be added will be displayed. Select Canon MG3500 series for which "Canon IJ Network" is displayed in the Kind field, and then click [Add]. After adding the printer, click [Next].
Add Printer Print Head Alignment Recommended Setup Complete STEP 4 Information	If printers that can be added are not displayed or if you are not sure how to use the screen, click [Help].
	Add Printer Help
	Next

18. 在新增印表機畫面選擇「Kind」為「Canon IJ Network」印表機,確定「Use」為「Canon MX470 series」

	0.108
P 🥨 💻	Q (2019)
IP Windows	技尽
名稱	∧ 種類
Canon MF6100 Series	Bonjour
Canon MG5500 series	Bonjour 多功能
Janon MX470 series	Bonjour 多功能
Janon MA470 series	Ganon IJ Network
Arm - Cases MV470 ander	
名稿: Canon MX470 series	3
25 ML -	
TWINE -	
使用: Canon MX470 serie	8
	大成





20. 可自訂是否同意安裝調查程式



21. 建議按「Execute」執行列印測試頁,完成後按「Next」

t Print rinter setup and software installation have been completed. printing will be performed to check the printer's operation. Load plain into the printer and click [Execute]. After test printing, click [Next]. Ip test printing, click [Next] instead of [Execute].
t Print rinter setup and software installation have been completed. printing will be performed to check the printer's operation. Load plain into the printer and click [Execute]. After test printing, click [Next]. Ip test printing, click [Next] instead of [Execute].
rinter setup and software installation have been completed. printing will be performed to check the printer's operation. Load plain into the printer and click [Execute]. After test printing, click [Next]. ip test printing, click [Next] instead of [Execute].
printing will be performed to check the printer's operation. Load plain into the printer and click [Execute]. After test printing, click [Next]. ip test printing, click [Next] instead of [Execute].
ip test printing, click [Next] instead of [Execute].
int error occurs, follow the on-screen instructions to start the setup
<b>S</b>
Execute
Next

# 22. 安裝完成



-完-