使用智能電話作臨時無線基地台並修改 IPv6(MG3570)

當印表機連接到無線存取點後,但無法獲取有效的 IPv4 位址時,您可將印表機的 TCP/IP 設定成禁用 IPv6,並且僅啟用 IPv4,讓印表機獲取有效的 IPv4 位址。 由於要禁用 IPv6 的話,需要在遠端介面(Remote UI)下設定,但要登入遠端介面,需先有一個有效的網路,因此可使用智能電話作臨時無線基地台,臨時建立 一個有效的網路,讓您可以登入印表機的遠端介面修改 IPv6 設定。

參考以下網址將智能電話作臨時無線基地台:

● 如使用 iPhone 裝置,請參考以下網址: https://support.apple.com/zh-hk/HT204023

● 如使用 Android 裝置,請參考以下網址中的「開啟並使用可攜式 Wi-Fi 無線基地台功能」:

https://support.google.com/nexus/answer/2812516?hl=zh-Hant

當智能電話的無線基地台功能開啟後,則可讓「另外一部的智能電話」、「平板電腦」或「有 Wi-Fi 無線功能的電腦」,使用 Wi-Fi 加入您的個人熱點,以下為不同裝置的設定方法:

使用另外一部智能電話或平板電腦

使用有 Wi-Fi 無線功能的電腦

使用另外一部智能電話或平板電腦:

1. 點一下「設定」>Wi-Fi,並選擇連接至作為無線基地台的智能手機

如使用i	如使用 iOS 智能手機/裝置:		如	使用 Android 智能	能手機/裝置:
•••••	上午9:41	100%			" []" 🕌 🛑 52% 3:27
<設定	Wi-Fi		÷	Wi-Fi	Q :
Wi-Fi				開啟	•
選擇網路…				CHK-CC_New 正在取得 IP 位址	
Wi-Fi_netwo	rk	≈ (j)		MT_Guest	
WI-FI_secure 其他…	9		•	Canon_ij_Setup	
			•	CII_SnS-guest	
詢問是否加入網 路	路	\bigcirc		MT_General	
將會自動加入已知的約須手動選擇網路。	周路。若沒有可用的	已知網路,您就必	₹.	CII_SnS	
			▼4	CII_SnS_5Ghz	
				CP910-4A243A	

2. 参考以下網頁「利用 Canon PRINT Inkjet / SELPLHY 應用程式作網路設定」進行 設定

http://www.canon.com.hk/tc/product/catalog/productItemDetails.do?prrfnbr=2 00693&tagID=5309 3. 在 Canon PRINT Inkjet / SELPHY 內同樣選擇連接至作為無線基地台的智能電



4. 完成後註冊印表機



5. 註冊完成後,返回主頁,並按「MG3500 series」

• +	Canon Inkjet/	י ⊡ PRINT SELPHY	• • • 53	3% 3:06 (j)
	MG350	0 series		
			~	
相片列印]		文件列印	
日本 「市本				
雲端				
道 擷取				
合 行動	裝置設定			
\bigtriangledown	(C		:

6. 按「印表機資訊」,按後將開啟智能裝置的瀏覽器,並進入 MG3570 的 Remote UI (遠端介面)

🔍 🖬 👘 🔽 着 53	% 3:06
PRINT - 印表機設定 -	
MG3500 series IP 位址 192.168.1.102 MAC 位址 18:0C:AC:3C:12:47	
ひ 表機資訊	C
□ ↓ 線上手冊	Q
▲ 型水型號編號	þ
印表機資訊傳送設定 1	>
	:

7. 進入 Remote UI (遠端介面)後,如按「Network Configuration」

		⊕, 💎	A 🗎 92% 3:56
Ð	192.168.1.104/	index.html	≡ :
	IJ	力能表	
印表	幾 狀態		
實用種	呈式		
AirPr	int設定		
Goog	le Cloud Print設定		
韌體	更新		
3	戶冊(線上) 🔗		
> Net	work Configuration		
	\bigtriangledown	0	

註:若出現如下的管理員密碼驗證畫面,請輸入印表機驗證密碼,驗證密碼 預設為印表機的機身編號

0			" " \	73%	1:13
ন্থ	https://19	2.168.1.	102/rui/loı	Ĩ	:
		管理員密	碼驗證		
需要	₽密碼驗證 。	請輸入管	理員密碼。		
			關於密	邵碼	
輸ノ	、密碼(4到3:	2個英數字	『元)		
		Oł	۲		
	\triangleleft	С)		

8. 左下角「Advanced」

▲▲▲■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■<	/netconf.html	□ □ ▼
Canon	Network C	Configuration
Canon MG3500 series Network Confi Copyright CANON INC. 2003-2013 All Rights Reserved.	guration	Last update : 2015/10/07 15:07:13
Printer Name:	Canon MG3500 series	
Firmware Version:	1.030	
LAN Connection Type	: Wireless LAN / IPv4	
Signal Level:	81%	_
Link Quality:	58%	_
		A dynamical with

9. 按「Network Settings」

•			· [] · 💙 🖌 🛢 53% 3:07	
𝔅 192.16	68.1.102/English/page	es_MacUS/_top.html		
Network Configuration Basic Information	Last update : 2015/10/07 15:07:27 Printer Information		\$?	
Top Page Network Settings Other Settings Admin Password	Printer Name: Firmware Version: Network Printer Name: Bonjour Service Name:	Canon MG3500 series 1.030 3C1247000000 Canon MG3500 series		0
	Status LAN Connection Type: MAC Address (AirPort ID): IPv4 Address: Subnet Mask: Router:	Wireless LAN / IPv4 18-0C-AC-3C-12-47 192.168.1.102 255.255.255.0 192.168.1.1		\bigtriangledown

10. 剔選「Disable IPv6」, 然後按「OK」



11. 等候更改設定,完成後會回到步驟



12. 當完成後,可以後將智能電話/平板電腦的 Wi-Fi 連接恢復至您的 Router 路 由器。而智能裝置上的熱點功能則可關閉。

13. 現可使用原有的 Router 路由器進行連線

-完-

如使用有 Wi-Fi 無線功能的電腦:

 選擇連接至作為無線基地台的智能手機,根據不同作業系統和無線網路卡連 接介面也不同,下圖僅為參考:

Networks	
View Connection Settings	
Airplane mode	
Off	
Wi-Fi	
On	
CHK-CC_New Connected	
AndroidAP12	
II CII_SnS	
CII_SnS_5Ghz	
.II MT_General	

 参考以下網頁「無需 USB 線安裝網路驅動程式 Cableless setup for wireless printer driver (只適用於具備 Wi-Fi 功能的手提電腦 Applicable on Notebook with Wi-Fi)」部份 http://www.canon.com.hk/tc/product/catalog/productItemDetails.do?prrfnbr=2

<u>http://www.canon.com.hk/tc/product/catalog/productItemDetails.do?prfhbr=</u> 00693&tagID=5309

- 3. 在安裝網路驅動程式內同樣選擇連接至作為無線基地台的智能裝置
- 連接成功的話,請參看以下網址列印輸出網路設定資訊,以查看打印機的 IP 位址: <u>http://ugp01.c-ij.com/ij/webmanual/Manual/W/MG3500%20series/TC/NTR/ntr</u> <u>settings1200.html</u>

5. 在瀏覽器上,如下圖在網址列輸入打印機的 IP 位置

		- 8 ×
C (192.168.1.102 index.html (↑ ★ ₿
Menu	Printer status	
Printer status	Ready to print.	
Utilities		
AirPrint settings	Estimated ink levels	
Google Cloud Print setup		
Firmware update	Black	
Manual (Online)	Ink number Order my ink now	
	*	
Network Configuration		

6. 進入 MG3570 的 Remote UI (遠端介面)後,如下圖到按左下角「Network Configuration」

← ⓒ @ http://192.168.1.102/index.html ♀	C S Remote UI ×
Menu	Printer status
Printer status	Ready to print.
Utilities	
AirPrint settings	Estimated ink levels
Google Cloud Print setup	Color
Firmware update	U Black
Manual (Online)	Ink number Order my ink now
	k.
> Network Configuration	

7. 按「Advance」

/192.168.1.102/netconf.html	ク・C Canon MG3500 series Netw ×	
Canon	Network Co	onfiguration
Canon MG3500 series Network Configuration Copyright CANON INC. 2003-2013 All Rights Reserved.		Last update : 2015/10.07 15:13:15
Printer Name:	Canon MG3500 series	
Firmware Version:	1.030	
LAN Connection Type:	Wireless LAN / IPv4	
Signal Strength:	67%	
Link Quality:	50%	
		# Advanced #
D		

註:若出現如下的管理員密碼驗證畫面,請輸入印表機驗證密碼,驗證密碼 預設為印表機的機身編號

← → @ https://192.168.1	-	.□ × ħ★☆
Menu	Admin password authentication	
Details When a password is set, password entry will be requested. About the password	Password authentication is required. Enter the administrato password. Enter password (4-32 alphanumerics)	ı r
Ç		
	οκ	

8. 按「Network Settings」

← → Ø http://192.168.1.102/En	nglish/pages_WinUS/_top.html 🔎 + 🖒 💋 Canon MG	550 series Netw ×	- = = n *
Network Configuration Basic Information	Last update : 2015/1007 15:13:21 Printer Information		\$?
r Top Page Printer Name:		Canon MG3500 series	
Network Settings	Firmware Version:	1.030	
Other Settings	Network Printer Name:	3C1247000000	
A day's Deserved	Bonjour Service Name:	Canon MG3500 series	
Admin Password			
	Status	b.	
	LAN Connection Type:	Wireless LAN / IPv4	
	MAC Address:	18-0C-AC-3C-12-47	
	IPv4 Address:	192.168.1.102	
	IPv4 Subnet Mask:	255.255.255.0	
	IPv4 Default Gateway:	192.168.1.1	
	Communication mode:	Infrastructure	
	SSID:	CHK-CC_New	
	Encryption Method:	Use WPA2	
	Signal Strength:	72%	
	Link Quality:	52%	
	Transmission Rate:	81 Mbps	

9. 剔選「Disable IPv6」,然後按「OK」

(-) (2) http://192.168.1.102/En	nglish/pages_WinUS/_lan_set.html	Canon MG3500 series Netw X		- = <mark>×</mark> n * a
Network Configuration	Wetwork Settings			
III Basic Information III	Set up printer for use with LAN.			:: OK :: Cancel :: ?
E Top Page	Wireless LAN active/inactive	_		
P Network Settings E Other Settings	 Do not use LAN 			D
E Admin Password	• Use wireless LAN:	Network Type: SSID: Encryption Method:	Infrastructure CHK-CC_New Use WPA2 Modify	
	E			
	Change IPv4/IPv6			
	Use IPv4:	• Get IPv4 address automatically • Use following IPv4 address: IPv4 Address: IPv4 Subnet Mask: IPv4 Default Gateway:	192 168 1 102 255 255 255 0 192 168 1 1	
	• Disable IPv6:			
	O Use IPv6:	IPv6 Address: IPv6 Subnet Prefix Length: IPv6 Default Gateway: IPsec:	Unknown Unknown Do not use Modify	~

10. 等候更改設定,完成後會回到步驟

🗲 💿 👩 http://192.108.11.02/En.glah/page, WinUS/ Jan, set, reload.html ρ = d 🧃 Canon MG3500 series Hetw X	- " × n * ¤
W Now setting	
Changing the settings Please wait a while.	
	Х
	la I

- 11. 當完成後,可以後將電腦的 Wi-Fi 連接恢復至您的 Router 路由器。而智能裝置上的熱點功能則可關閉
- 12. 到控制台->裝置和印表機,將電腦原有的「Canon MG3500...」全部移除(如 有)



13. 現可重新安裝驅動程式,並使用原有的 Router 路由器進行連線