<u>在 MAC OSX 以 USB 接駁安裝 MF416dw 驅動程式步驟 (以 OSX 10.11 作示範)</u> MF416dw printer driver Installation Guide for MAC OSX via USB (OSX 10.11 as example)

注意: 安裝驅動程式前請勿接駁 USB 線, 以免系統發生錯誤

Caution: Prior to the installation, please do not connect the USB port to avoid system error

1. 到佳能網站 <u>https://hk.canon/en/support</u>,選擇相關的印表機型號及下載印表機的驅動程式 Go to: <u>https://hk.canon/en/support</u>, select related printer model, then download the printer driver

Search Support For Your Product

MF416	Q
imageCLASS MF416dw	

- 選擇並下載以下檔案
 Choose and download below files:
 - 打印機驅動程式 / Printer Driver

MF Printer Driver & Utilities for Macintosh V10.11.1 [Mac OS : 10.8/10.9/10.10/10.11/10.12/10.13/10.14]

- 掃描程式 / Scanner Software

Scanner Driver & Utilities for Macintosh V2.15.0 [Mac OS : 10.9/10.10/10.11/10.12/10.13/10.14]

3. 開啟下載檔案「UFRII LT Printer Driver 」,進入「SFP」文件夾 Open "UFRII LT Printer Driver", and then open "SFP"

,	4 14-14	
ζ	1 item	_
SFP		
Mac_UFRIILT_V140_00		

開啓"UFRII_LT_***.pkg"文件開始安裝設定
 Open "UFRII_LT_***.pkg" to start the driver installation

• • •		
•	2 items	
		
Documents	MF_Printer_Installer.pkg	
Mac_MF_Ver1060_00		

5. 按「Continue」 Click "Continue"

	Software License Agreement
 Introduction License Destination Select 	CANON SOFTWARE LICENSE AGREEMENT IMPORTANT
 Installation Type Installation Summary 	This is a legal agreement ("Agreement") between you and Canon Inc. ("Canon") and governing your use of Canon's software programs including the related manuals or any printed material thereof (the "SOFTWARE") for certain Canon's copying machines, printers and multifunctional peripherals (the "Products"). READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AND RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLING THE SOFTWARE. BY CLICKING THE BUTTON INDICATING YOUR ACCEPTANCE AS STATED BELOW OR INSTALLING THE SOFTWARE, YOU AGREE TO BE BOUND BY THE TERMS AND CONDITIONS OF THIS AGREEMENT. IF YOU DO NOT AGREE TO THE FOLLOWING TERMS AND CONDITIONS OF THIS AGREEMENT, DO NOT USE THE SOFTWARE.
V	GRANT OF LICENSE Canon grants you a personal, limited and non-exclusive license to use ("use" as used herein shall include storing, loading, installing, accessing, executing or displavina) the SOFTWARE solely for the use with Products only on computers Print Go Back Continue

6. 按「Agree」 Click "Agree"

	the software lie	ense agreement.					
	Click Agree to c	ontinue or click Disagr	ee to cancel the in	stallat	ion and		1
• LIC	quit the installe	•					
• De							
 Ins 	Read License		Disagr	ee	Agree	d	
 Ins 						's	
		RESTRICTIONS DESCRIPTIONS DESCR	BED IN THIS AGREEM CLICKING THE BUT	ENT B	EFORE INSTAL	YOUR	
	0	RESTRICTIONS DESCRI THE SOFTWARE. BY ACCEPTANCE AS STATEL AGREE TO BE BOUND AGREEMENT. IF YOU DO CONDITIONS OF THIS A	BED IN THIS AGREEM CLICKING THE BUT DELOW OR INSTALL BY THE TERMS AN O NOT AGREE TO THE GREEMENT, DO NOT	ENT BI TON I ING TH CON FOLLO	EFORE INSTAL INDICATING E SOFTWARE DITIONS OF DWING TERMS E SOFTWARE.	YOUR YOUR YOU THIS S AND	

7. 按「Install」 Click "Install"



8. 輸入登入名稱及密碼(如出現以下畫面)

Enter the login user name and password (If this screen is shown below)

your passw	ord to allow this.
Username:	Call Center
Password:	
	Cancel Install Software

9. 按「Close」 Click "Close"

	The installation was completed successfully.
IntroductionLicenseDestination Select	Add Printer
 Installation Type Installation Summary 	If you are using an old version of the driver, your printer may have been deleted. If the printer you are using has been deleted, add it again. See Printer Driver Guide for more information on how to add printers.
	Go Back Close

10. 完成安裝驅動程式後需新增印表機,使用 USB 線連接印表機與電腦,然後開啟印表機,按一下電腦左上角< [●] >圖 案,選擇<系統偏好設定>,再選擇<印表機和掃描器>

After finished the driver installation, connect the USB cable with printer and computer, turn on the printer, please click the top left corner of the computer < is > icon, click <System Preferences>, and then click <Printers and Scanners>



 於〔列印和掃描器 (Printers& Scanners)〕 視窗,按一下「+」按鈕加入印表機 In the [Printers & Scanners] window, click the "+" button to register the printer

N Click	lo printers are available. : Add (+) to set up a printer.		
Default printer:	Last Printer Used	0	2
	N Click Default printer: Default paper size:	No printers are available. Click Add (+) to set up a printer. Default printer: Last Printer Used Default paper size: A4	No printers are available. Click Add (+) to set up a printer. Default printer: Last Printer Used C Default paper size: A4

12. 名稱選擇「Canon MF410 Series」,種類「USB Multifunction」,確認「使用(Use)」為「Canon MF410 Series」,然後 按「加入(Add)」

Choose "Name" as "Canon MF410 Series", confirm "Kind" as "USB Multifunction" and "Use" is "Canon MF410 Series", and then click "Add"

2			0 502	rch	
fault IP M	/indows		Sea	rch	
	indows		364		
Name			^	Kind	
Canon MF410	Series			Bonjour Scanne	r
Canon MF410	Series		l	JSB Multifuncti	on
Canon MF410	Series FAX		l	JSB Multifunction	on
Marrie	Capon ME410 So	rioc			
Name:	Canon MF410 Se	nes			
Location:	CHK-CC的MacBo	ook Pro			
	Capon ME410 Se	arias			
100	Calloff MF410 36	51165			
Use:					Add
Use:				(Add

*** 如「使用(Use)」不是「Canon MF410 Series」,請按以下步驟設定*** *** If "Use" is not "Canon MF410 Series", please refer to the steps below

a) 請如下圖打開「使用(Use)」的選單,選擇"Select Software" Please open "Use", and then choose "Select Software"

Choose a Driver	
Auto Select ✓ Generic PCL Printer Select Software	
Other	

b) 輸入 MF410 以搜尋「Canon MF410 Series」 Enter "MF410", and then choose "Canon MF 410 Series"

		Q MF4	10	(8
Canon MF410 Series					
Canon MF4100 Series					
Canon MF4100 Series FAX	C				
			Cancel	ОК	

13. 新增印表機完成,驅動程式安裝完畢

After the printer is added, driver installation is completed

Printers		Print Scan	
Canon MF410 Series	E.	Canon MF410 Series	
		Open Print Queue.	
		Options & Supplies	
	Location:	CHK-CC的MacBook Pro	
	Kind:	Canon MF410 Series	
	Status:	Idle	
+	Share this printe	er on the network	Sharing Preferences
T -	Default printer:	Last Printer Used	.
	Default paper size:	A4	

