### <u>LBP712Cx 在 Windows 透過 USB 連線連接印表機之驅動程式步驟</u> <u>Driver installation procedure for LBP712Cx in Windows (Via USB)</u>

\*\*注意: 安裝驅動程式前請勿接駁 USB 線,以免系統發生錯誤\*\* \*\* Please don't plug the USB cable until the driver asked to do so\*\*

下載及安裝步驟

Driver download and Installation procedure

**1.** 到佳能網站 <u>http://support-hk.canon-asia.com/</u>,選擇相關的印表機型號及下載 印表機的驅動程式

Go to: <u>http://support-hk.canon-asia.com/</u> , select related printer model, then download the printer driver

•

٧

۳

SUPPORT & DOWNLOAD

Select your product from the menus below:

1. Choose a product category
Laser Printers
▼

2. Choose a product series ImageCLASS

3. Choose a product model imageCLASS LBP712Cx

4. Choose type of document Drivers & Softwares

### 2. 選擇並下載以下檔案

Choose and download below files:

- 打印機驅動程式〔UFRII\_Driver\_VXXXXXX.exe〕 Printer Driver〔UFRII\_Driver\_VXXXXXX.exe〕  下載的文件以自解壓縮檔檔案(.exe 格式)保存在指定的文件夾中,打開文件解壓縮。
 將在同一文件夾中創建新文件夾。新文件夾的名稱與解壓縮文件的名稱相同,進 入新文件夾開啟「Setup.exe」開始安裝

Open the downloaded file, a same name new folder will be created. Go into new folder open "Setup.exe" start installation

	晚 > 下載 > UFRII_Driver_V3012_W	4_ukEN_01			✔ ひ 搜尋 UFRII_Driver_V30	12_W6
- 仙連方取	名稱	修改日期	類型	大小		
	Driver	2017/6/9 下午 02:31	檔案資料夾			
Creative Cloud Files	misc	2017/6/9 下午 02:31	檔案資料夾 LITML 庫田程式	40 KB		
loneDrive 🍊	Setup	2017/4/4 上午 11:32 2017/4/6 上午 12:00	應用程式	49 KB 4,461 KB		
🥒 本機	🔂 Setup	2017/4/6 上午 12:00	組態設定	1 KB		
◆ 網路						
國項目						
選擇「Ye	S _					
Choose "	/ec"					
뽳 UFR II	Printer Driver -	Ver. 30.12			×	
License A Please r carefully	greement ead the following li ⁄. Click [Yes] to agr	cense agreement comp ee to the license agree	pletely and ement.			
CANO	SOFTWARE	LICENSE AGRE	FMENT		^	
erne.						
IMPO	RTANT					
This is ("Cano includii "SOFTV multifu	a legal agree n") and gove ng the relate VARE") for o nctional periph	ment ("Agreeme rning your use d manuals or a ertain Canon's nerals (the "Produ	ent") betw e of Car any print copying ucts").	ween you and non's software ted material t machines, p	Canon Inc. programs hereof (the rinters and	
martina			AND AL			
READ		AND UNDERST	THIC	AGREEMENT		

3.

4. 選擇「USB Connection」,按「Next」

UFR II Printer Driver -	- Ver. 30.12	$\times$
The UFR II printer driver wi Select a setup method, an	ill be installed on your computer. Id then click [Next].	
Printer Setup	○ Standard	
	Search for printers on the network and install.	
	Reactivate Printers in the Sleep Mode and Search	h
	<ul> <li>Custom</li> <li>Specify a port or an IP address manually to install or local or network printers.</li> <li>You can also specify other settings, such as setting a shared printer.</li> </ul>	drivers of a printer as
	• USB Connection Connect the printer with a USB cable and install.	

5. 勾選「UFR II Printer Driver」,按「Next」 Select "UFR II Printer Driver", press "Next"

뽳 UFR II Printer Driver - Ver. 30.12		×
Select Process		-
Select the items to install and the process to insta driver.	all the printer	
UFR II Printer Driver		
Process to Install Printer Driver		
Add New Printers and Update Existing Printers	inter Drivers	
O Add New Printers		
O Update Existing Printer Drivers		
Canon Driver Information Assist Service		
By installing this service, you will be able to ret ID Management and User Authentication from	rieve device information and pe your computer when using shar	erform Department red printers.
D Management and User Authentication from	your computer when using shar	ed printers.

#### 勾選「Canon LBP712C UFR II」,按「Next」 Select "Canon LBP712C UFR II", press "Next" WFR II Printer Driver - Ver. 30.12 $\times$ Select Printers to Install Select the printers to add, and then click [Next]. Printer List: Canon LBP8750 UFR II ^ Canon LBP252 UFR II Canon LBP253 UFR II Canon LBP6650/3470 UFR II Canon LBP6670 UFR II Canon LBP6750/3560 UFR II Canon LBP6780/3580 UFR II Canon LBP8780 UFR II Canon LBP310/311/312 UFR II Canon LBP351/352 UFR II Canon LBP611C UFR II Canon LBP612C/613C UFR II Canon LBP7660C UFR II Canon LBP7680C/5280 UFR II Canon LBP653C/654C UFR II Canon LBP843C/841C UFR II Canon LBP710C UFR II Canon LBP7780C/5480 UFR II Canon LBP712C UFR II V < Back Next > Cancel

# 7. Port 位置選擇「USBXXX」,按「Next」

6.

# Port select "USBXXX", press "Next"

📚 UFR II Printer Driver - Ver. 30	.12 >
Printer Information Set the port to be used for the selec	cted printer.
Also, you can specify a name for th	e printer.
Selected Printer:	Canon LBP712C UFR II
Use Driver:	Canon UFR II Printer Driver Ver. 30.12
Port:	USB006 ~
	Add Port
Printer Name:	Canon LBP712C UFR II
Set as Default Use as Shared Printer	
Shared Name:	
Devices: 1 (1 to 200)	Current Printer:
	Number of Frinters to Set.

# 8. 確認新增印表機資料,按「Start」

onfir	rm new printer info	rmation, press "Start"	,
UFR	II Printer Driver - Ver. 30.12		×
The set * Ins	tup program will install the driver tallation cannot be canceled once	s with the following settings. started.	
Printer	List for Driver Installation:		
Add	Printer Name Canon LBP712C UFR II	Driver Canon LBP712C UFR II	Port USB006
<			>
		< Back	Start Cancel

## 9. 等待安裝程序完成



10. 按「Restart」重啟電腦,完成安裝





-完--End-