使用乙太網絡連接線接駁到印表機及開啟印表機

Connect the machine to a router by using a LAN cable and turn on computer



先將打印機連接到網路,詳細可參考以下步驟 Connect printer to network first, please refer to following procedure

- 開啟印表機 Turn on the printer
- 在主畫面中點選「功能表」
 Tap "Menu" in the Home Screen
- 3. 點選「網路設定」 Tap "Network Settings"
- 4. 點選「選擇有線/無線區域網路」 Tap "Select Wired / Wireless LAN"
- 5. 點選 <有線區域網路> Tap "Wired LAN"

 到佳能網站 <u>https://hk.canon/en/support</u>,選擇相關的印表機型號及下載印表機的驅動程式 Go to: <u>https://hk.canon/en/support</u>, select related printer model, then download the printer driver

Search Support For Your Product

264	۹
imageCLASS MF 264 dw	

選擇並下載以下檔案
 Choose and download below files:

- 打印機驅動程式 / Printer Driver [Windows xxbit] MF269dw/MF267dw/MF266dn/MF264dw/MF261d MFDrivers (UFRII LT / Generic Plus PCL6 / Generic FAX / ScanGear)

- 掃描程式/ Scanning Software [Windows 32bit & 64bit] MF Scan Utility Ver.1.x.0.0

- 下載完成後,打開驅動程式 安裝檔案
 Open driver installation file after downloaded
- 4. 按「Next >」



5. 按「Yes」

Click "Yes"

/IF Drivers	>
License Agreement Please read the following license agreement completely and carefully. Click [Yes] to agree to the license agreement.	
CANON SOFTWARE LICENSE AGREEMENT	^
IMPORTANT	T
This is a legal agreement ("Agreement") between you and Canon Inc. ("Canon") and governing your use of Canon's software programs including the related manuals or any printed material thereof (the "SOFTWARE") for certain Canon's copying machines, printers and multifunctional peripherals (the "Products").	
READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AND RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLING THE SOFTWARE. BY CLICKING THE BUTTON INDICATING YOUR ACCEPTANCE AS STATED BELOW OR INSTALLING	~
Do you agree to the terms in license agreement?	
< Back Yes No	

6. 選擇「Network Connection (for Network Models)」,按「Next >」 Select "Network Connection (for Network Models)", click "Next >"

MF Drivers			×
Select the Type of Connection Select the type of connection between the dev	vice and your com	outer.	
C USB Connection			
 Network Connection (for Network Models) 	>		
	< Back	Next >	Cancel

7. 按「是」

Click "Yes"

MF Drivers	\times
To use this program, you must remove all firewall blocks set against this program. Do you want to change the Windows Firewall settings so that the Windows Firewall block will be removed? To make this setting effective, it is also necessary to allow exceptions in Windows Firewall.	
是(Y) 否(N)	

8. 選擇「MF260 Series」(以 MF410 Series 為例子),按「Next >」(如清單沒有印表機,請選「Search by IP Address」方法連接或聯絡客戶服務熱線 31912333 尋求支援)

Select "MF260 Series" (MF410 Series as example), click "Next >"(If there is no printer on the list, please select "Search by IP Address" method to connect or contact customer service hotline 31912333 to seek for support)

MF Drivers	×
Select Device Select a target device to ins	tall the drivers.
 Select Device Select Driver Confirm Settings Install Set Default Printer Print Test Page 	Select the device from the device list and click [Next]. If the device is not listed in the device list, click [Search by IP Address] and specify the device IP address manually. Device List: Device Name MAC Address IP Address Location MF410 Series COMP CO ST CO ST CO ST 192.168.1.106
	Search by IP Address Update Device List
Search Option	< Back Next > Cancel

9. 確認已剔選「Printer」「Fax (for Supported Models」「Scanner」(以 MF410 Series 為例子),按「Next >」

Confirm the "Printer" "Fax for Supported Models" "Scanner" box is checked(MF410 Series as example), click "Next >"



10. 選擇「UFR II Printer Driver」(以 MF410 Series 為例子),按「Next >」 Select "UFR II Printer Driver" (MF410 Series as example), click "Next >"

MF Drivers	\times
Select Driver Select the drivers to install.	
 Select Device Select Driver Confirm Settings Install Set Default Printer Print Test Page 	Target Device MF410 Series Printer Drivers to Install: UFR II Printer Driver PCL6 Printer Driver PS3 Printer Driver
	< Back Next > Cancel

11. 按「Next >」(以 MF410 Series 為例子)

Click "Next >" (MF410 Series as example)

Confirm Settings Confirm the following set	tting details.
 Select Device Select Driver Confirm Settings Install Set Default Printer Print Test Page 	You can change the printer name. If you specify this printer as a shared printer, you can specify the shared printer name and set an additional driver (alternate driver). Confirm the settings, and then click [Next]. Printer Port: CNMFNP_0040000F00E4+ Driver: Canon MF410 Series UFR II Printer Name: Canon MF410 Series UFR II Use as Shared Printer Shared Name:
	Drivers to Add
	Current Device: 1

12. 按「Start」(以 MF410 Series 為例子)

Click "Start>" (MF410 Series as example)

MF Drivers Confirm Settings The setup program will insta	all the drivers with the following settings.
 Select Device Select Driver Confirm Settings Install Set Default Printer Print Test Page 	Items for Installation: Port: CNMFNP_0045005F09E4 Printer: Canon MF410 Series UFR II Driver: Canon MF410 Series UFR II Port: CNMFNP_0045005F09E4 Fax: Canon MF410 Series (FAX) Driver: Canon Generic FAX Driver (FAX) Port: CNMFNPSCAN_0045005F09E4 Scanner: Canon MF410 Series
	< Back Start Cancel

13. 請等待安裝精靈成完安裝

Please wait for the setup wizard to accomplish installation

M	⁻ Drivers		×
1	Install The program features you sele	ected are l	being installed.
1. 2. 3. 4. 5. 6.	Select Device Select Driver Confirm Settings Install Set Default Printer Print Test Page	٩	Setup Wizard is installing the MF drivers. Please wait Status: Installing printer driver
			Cancel

14. 選擇「Installed Printer: Canon MF260 Series UFR II」(以 MF410 Series 為例子),按「<u>N</u>ext >」 Select "Installed Printer: Canon MF260 Series UFR II" (MF410 Series as example), click "<u>N</u>ext >"



 可剔選「Printer: Canon MF260 Series UFR II」以(MF410 Series 為例子)進行列印測試頁,按「Exit」 Can check the box at "Printer: Canon MF260 Series UFR II" (MF410 Series as example) to print a test page, click "Exit"



安裝掃描軟件MF Scan Utility MF Scan Utility installation procedure

16. 執行檔案〔MFScanUtility_*****_EN.exe〕按「Next」 Run the file [MFScanUtility_*****_EN.exe] , click "Next"



17. 按「Yes」

Click "Yes"

CANON SOFTWARE LICENSE AGREEMENT	^
IMPORTANT	
This is a legal agreement ("Agreement") between you and Canon Inc. ("Canon") and governing your use of Canon's software programs including the related manuals or any printed material thereof (the "SOFTWARE") for certain Canon's copying machines, printers and multifunctional peripherals (the "Products").	
READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AND RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLING THE SOFTWARE. BY CLICKING THE BUTTON INDICATING YOUR ACCEPTANCE AS STATED BELOW OR INSTALLING THE SOFTWARE, YOU AGREE TO BE BOUND BY THE TERMS AND CONDITIONS OF THIS AGREEMENT. IF YOU DO NOT AGREE TO THE FOLLOWING TERMS AND CONDITIONS OF THIS AGREEMENT, DO NOT USE THE SOFTWARE.	~
you accept the agreement, click [Yes]. If you click [No], the installation of Canon N	١F
can Utility will be canceled.	
can Utility will be canceled.	

18. 按「Complete」 Click "Complete"



-完--End-