<u>在 Windows 以無線方式安裝及連接 PIXMA TS3470 打印機(以 Windows 10 作示範)</u> Installing PIXMA TS3470 on Windows via WiFi connection (Use Windows 10 as example)

*請開啟打印機並確保電腦已連接互聯網

*Please turn on the printer and make sure computer already connected to the internet

請參考以下簡易無線連接方法設定印表機的無線功能

Please refer to following Easy wireless connect to setup the Wi-Fi of printer

簡易無線連接

Easy wireless connect

- 在智慧型手機或平板電腦安裝 Canon PRINT Inkjet/SELPHY
 Install Canon PRINT Inkjet/SELPHY on smartphone or table
 Android:
 <u>https://play.google.com/store/apps/details?id=jp.co.canon.bsd.ad.pixmaprint</u>
 iOS:
 <u>https://apps.apple.com/us/app/pixma-printing-solutions/id664425773</u>
- 2. 按住印表機上的**無線連接(Wireless connect)**按鈕(A),然後在 □ (B) 閃爍時釋放按鈕 Press and hold the **Wireless connect** button (A) on the printer, and then release the button when □ (B) flashes



3. 確保(P)及水平橫條(C)閃爍

Make sure (1) and the horizontal bars (C) flash.



按照智慧型手機或平板電腦上的說明進行操作。
 Follow instructions on your smartphone or tablet.

<u>按此参考詳細操作步驟</u> <u>Click here for detail instructions</u>

下載及安裝步驟 Driver download and installation procedure 安裝前請確保電腦及印表機已連到相同路由器 Please make sure the computer and printer are connected to the same router before installation

- 到以下佳能網站並下載印表機的驅動程式 <u>https://hk.canon/zh_HK/support/TS3470/model</u> Go to below Canon webpage and download the printer driver <u>https://hk.canon/en/support/TS3470/model</u>
- 選擇並下載以下檔案
 Choose and download below files
 E3400/TS3400 series MP Drivers Ver.1.xx (Windows)
- 3. 按上面網頁內的〔下載〕,下載完成後開啟該檔案安裝

Click [Download] in the webpage above, and then execute the file after download was completed

4. 按〔下一步〕

Click [Next]

Canon IJ Driver Installer	×
歡迎進入驅動程式安裝程式。 本程式將在您的電腦上安裝驅動程式。 請將印表機連接到您的電腦並確認印表機已開啟,然後按一下 [下一步]。 本程式會暫時新增至 Windows 防火牆允許的應用程式清單。	
設定	下一步

5. 選擇〔亞洲〕,按〔下一步〕

Select [Asia]; click [Next]

Canon IJ Driver Installer	Х
選擇居住地,然後按一下 [下一步]。	
居住地(P):	
美國, 加拿大, 拉丁美洲 歐洲, 中東, 非洲	
太平洋地區	
下一步	

6. 按〔是〕

Click [Yes]

终端使用者授櫂 + 奇,女实鞋+		^
エーロ・III文戦中 本使用授權合約 恋的軟體程式、 」)的其他資料調 是供用於列印的 参提及的軟體 、Ohta-ku、Tok	每2012年84,88月1-3月268月442日、 是您(個人或實體)與 Canon Inc. 之間的授權合約(簡稱「合約」),是關於(i)随同本合約提供給 相關的電子或線上手冊及其更新(統稱「軟體」),(ii)軟體或 Canon 噴墨印表機(簡稱「印表機 如表機的韌體更新(簡稱「資料更新」),及(iii)随同本合約提供或使用該軟體及其更新線上 數位格式之文字、影像、圖示和其他視覺表示(本軟體除外)(簡稱「內容資料」)的合約。以 資料更新和內容資料各自簡稱「官方授權軟體」。Canon 公司位於 30-2 Shimomaruko 3-chome yo 146-8501、Japan(簡稱「Canon」)。	
盡管本合約中有 5軟體」)。第3 罌軟體的授權資	任何相反的規定,官方授權軟體還包括本合約條款不適用的某些軟體模組和資源庫(「第三 E方軟體清單及其適用的使用條款可能在本合約結尾、相關說明文件(如使用者手冊)或官方授 「訊中指明。	
安一下隨本合約 司意遵守本合約 方授權軟體將不	提供的按鈕,表示您接受本合約,安裝本官方授權軟體,或者使用本官方授權軟體,表示您 的條款。如果您不同意接受本合約的條款,請不要按前述按鈕並立即關閉本安裝程式。本官 會安裝,同時您將不再享有使用本軟體的權利。您僅能在遵守以下條款的情況下使用本官方	~

7. 選擇連接方法為 Wi-Fi 的打印機,按〔下一步〕

Select the printer with connection method as Wi-Fi, click [Next]

Canon IJ Driver Instal	ler			X
找到印表機。 請從清單中選擇印表 值測到的印表機:	機,然後按一下 [下一步]。			
產品名稱	序號(最後 5 位數)	連接方法	IPv4 位址	IPv6
Iseries	****	Wi-Fi	192.168.1.133	-
<				>
			重新搜尋	
找不	到印表機		依 IP 位址搜尋	ł
				下一步

8. 正在安裝印表機驅動程式,請稍候 Installing the driver, please wait

Canon IJ Driver Installer	X
正在安裝	

9. 安裝完成,按〔結束〕

Driver installation was completed; click [Finish]

Canon IJ Driver Installer		Х
驅動程式安裝成功。		
印表桦之和。	Canon series	
-1-2C102-01149-		
位置:		
留言:		
		變更印表機資訊
✓ 設定為預設印表機		
		結束

-完--End-