LBP7110Cw 以無線 LAN 連線連接印表機之驅動程式步驟 (以 MAC OSX 10.10 作示範 The Driver installation procedure for LBP7110Cw (Via Wi-Fi)(MAC OSX 10.10 as sample)

注意:安裝驅動程式前請勿接駁 USB 線,以免系統發生錯誤 ** Please don't plug the USB cable until the driver asked to do so**

下載及安裝步驟

(Download and Driver Installation Procedure)

- 到佳能網站 <u>https://hk.canon/en/support</u>,選擇相關的印表機型號及下載印表機的 MF/LBP Network Setup Tool (Go to: <u>https://hk.canon/en/support</u>, select related printer model, then download the MF/LBP Network Setup Tool)
- 2. 開啟 Canon MF/LBP Network Setup Tool (Open "Canon MF/LBP Network Setup Tool")

	Aac_NWST_V211_00
Canon MF/LBP Network Setup Tool	Documents

3. 如出現如下畫面,請按「Open」(Choose "Open")

O	"Canon MF/LBP Ne downloaded from th open it?	twork Setup Tool" is an application ne Internet. Are you sure you want to
	"Canon MF/LBP Networ "Mac_NWST_V211_00 (image today at 10:10 an	k Setup Tool" is on the disk image 1).dmg". Google Chrome downloaded this dis n from support-hk.canon-asia.com.
	Don't warn me wi	nen opening applications on this disk in
?	Cancel	Show Web Page Oper

4. 選擇「Wireless LAN Connection」(Choose "Wireless LAN Connection")

Select the type of c	Canon	MF/LBP Netwo	rk Setup Tool I your computer.
<u> </u>			O Wired LAN Connection
 ")	((_))	("	• Wireless LAN Connection
Useful Tips	Change	e Settings	Continue

5. 選擇「<u>Y</u>es, I want to configure network settings」 (Choose "<u>Y</u>es, I want to configure network settings")

*	(()			
2. Are you sure you	u want to configure	network settings	for the printer?	
)))	(um		
	configure network	settings.		
OYes, I want to		atuarly aattinga		
OYes, I want to ONo, I do not v	vant to configure ne	etwork settings.		
• Yes, I want to No, I do not v	vant to configure ne	etwork settings.		

6. 選擇「Easy Setup」(Choose "Easy Setup")



7. 選擇「My wireless LAN access point does not have a WPS button or I cannot find the button 」 (Choose "My wireless LAN access point does not have a WPS button or I cannot find the button")



8. 請使用 USB 電纜線連接印表機和電腦,開啟印表機後按「Continue」(Connect printer and computer with the USB cable, and then turn on the printer)

• • •	Canon MF/LBP Network Setup Tool
Configure the netwo	ork settings using a USB cable.
0	 Turn on the printer. If the printer is already on, turn it off, and then turn it back on again after a moment.
	$\overline{\mathbf{v}}$
	 2. Connect the printer to your computer using a USB cable. * If the printer is already connected with a USB cable, disconnect the USB cable from the printer, and then connect it to the printer again.
	$\overline{\mathbf{v}}$
	3. Click [Continue] to go to next screen.
Useful Tips	Go Back Continue

9. 選擇您的網路,按「Continue」(Select your network, then choose "Continue")

etected Wireless LAN Access Points:	
SID	Security
est	WPA2-PSK
HK-CC_New	WPA2-PSK
CII_SnS	WPA2-PSK
CII_SnS-guest	None
IT_General	WPA2-PSK
Buest	WPA2-PSK
/T_Guest	WPA2-PSK
PO	WPA2-PSK
inksys E2500	WPA2-PSK
pom2014_wifi	WPA2-PSK
ne SSID may be printed on the wirele	ss LAN Search Again
cess point.	Configure Pottings Again

10. 如出現如下畫面,請輸入 Wi-Fi 網路金鑰 (Type your Network Key)

Network Key:	123
	Mask Network Key during Entry
	The network key may be printed on the wireless LAN access point.

11. 拔取 USB 電纜線,按「Continue」(Disconnect your USB cable, then choose "Continue")



12. 按「Exit」離開網路設定工具 (Choose "Exit" to exit the wizard)

Configuration of th	e network settings for the printer has ended.
To check if the p	inter has connected to the network correctly, refer to Useful Tips.
To save the ope	ation logs for Canon MF/LBP Network Setup Tool, click [Save Operation Lo
If you configured back on again.	the wireless LAN connection settings, turn the printer off, and then turn it
 This step is no steps on the pre 	necessary if the printer was already turned off and on when following the
* This step is no steps on the pre	necessary if the printer was already turned off and on when following the rious screen.
* This step is no steps on the pre	necessary if the printer was already turned off and on when following the rious screen.
* This step is no steps on the pre	necessary if the printer was already turned off and on when following the rious screen.
* This step is no steps on the pre	necessary if the printer was already turned off and on when following the rious screen.
* This step is no steps on the pre	necessary if the printer was already turned off and on when following the rious screen.

- 到佳能網站 <u>https://hk.canon/en/support</u>,選擇相關的印表機型號及下載印表機的 驅動程式 - UFTRII LT Printer Driver (Go to: <u>https://hk.canon/en/support</u>, select related printer model, then download the printer driver - UFTRII LT Printer Driver)
- 14. 開啟下載檔案「UFRII LT Printer Driver」,進入「SFP」文件夾 (Open "UFRII LT Printer Driver", then open "SFP")

•••	Mac_UFRIILT_V120_00	
SFP		

15. 開啓"UFRII_LT_***.pkg"文件開始安裝設定(Double Click / Open "UFRII_LT_***.pkg")

•••		SFP
	÷	
Documents	UFRII_LT_CARPS2_ Installer.pkg	

16. 按「Continue」(Choose "Continue")



17. 按「Continue」(Choose "Continue")

	Software License Agreement
- Interduction	English
	CANON SOFTWARE LICENSE ACREMENT
License	
Destination Select	IMPORTANT
Installation Type	This is a legal agreement ("Agreement") between you and Canon Inc. ("Canon", and opverning your use of Canon's software programs including the related manual
Installation	or any printed material thereof (the "SOFTWARE") for certain Canon's copying
Summary	machines, printers and multifunctional perpinerals (the "Products").
	READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AND RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLING THE SOFTWARE. BY CLICKING THE BUTTON INDICATING YOUF ACCEPTANCE AS STATED BELOW OR INSTALLING THE SOFTWARE, YOU AGREE TO BE BOUND BY THE TERMS AND CONDITIONS OF THIS AGREEMENT. IF YOU DO NOT AGREE TO THE FOLLOWING TERMS AND CONDITIONS OF THIS AGREEMENT, DO NOT USE THE SOFTWARE.
रप्र	 GRANT OF LICENSE Canon grants you a personal, limited and non-exclusive license to use ("use" a used herein shall include storing, loading, installing, accessing, executing o disolavino) the SOFTWARE solely for the use with Products only on computer
	Print Save Go Back Continue

18. 如出現以下畫面,按「Agree」(Choose "Agree")

	the software li	cense agreement.
 Inti 	Click Agree to	continue or click Disagree to cancel the installation and
• Lic	quit the Installe	r.
 De: 		
 Ins 	Read License	e Disagree Agree huak
Ins		į į į į į į į į į į į į į į į į į į į
		READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AND RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLING
	6	READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AND RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLING THE SOFTWARE. BY CLICKING THE BUTTON INDICATING YOUF ACCEPTANCE AS STATED BELOW OR INSTALLING THE SOFTWARE, YOU AGREE TO BE BOUND BY THE TERMS AND CONDITIONS OF THIS AGREEMENT. IF YOU DO NOT AGREE TO THE FOLLOWING TERMS AND CONDITIONS OF THIS AGREEMENT, DO NOT USE THE SOFTWARE.

19. 按「Install」(Choose "Install")



20. 按「Close」(Choose "Close")



 完成安裝驅動程式後需新增印表機,到「系統偏好設定(System Preference)」, 選「印表機與掃描器(Printers & Scanners)」(Go to "System Preference", then open "Printers & Scanners")



22. 選取左下角「+」按鈕,選「加入印表機或掃描器(Add Printer or Scanner)」 (Click "+", then choose "Add Printer or Scanner")

		(Q		
	請技	沒有可用的印表機 ∹一下「新増」(+)來設定印 表機。		
+ -	預設印表機:	最近使用的印表機	\$	
	石机在建一小	Δ4	÷) (?

名稱選擇「Canon LBP7100Cw」,種類「Bonjour」,確認「使用(Use)」為「Canon LBP7100C/7110C」,然後按「加入(Add))」("Name" chooses "Canon LBP7100Cw", "Kind" chooses "Bonjour". After you confirm "Use" is "Canon LBP7100C/7110C", then choose "Add")

首 值直	IP Windows	拘意
EL 10794	e in mindows	TTXL
稱		▲ 種類
anon LB	P7110Cw	Bonjour
名稱:	Canon LBP7110Cw	
位罟·		
位置:	Canon LBP/100C//110C	÷
位置: 使用:		
位置: 使用:		
位置: 使用:		

*** 如「使用(Use)」部份不是「Canon LBP7110***」,請按以下步驟設定** (*** If "Use" is not "Canon LBP7110***", please reference the steps below)**

a) 請如下圖打開「使用(Use)」的選單,選 Select Software (Open "Use", then choose "Select Software")

設值 傳算	E IP	Windows		 搜 君	
147				200	
名稱				▲ 種類	
Canon LE	P7110Cw	λ.		Bonjour	
名稱:	Canon	LBP7110Cv	N		
名稱:	Canon	LBP7110Cv	N		
名稱: 位置:	Canon	LBP7110Cv	v		
名稱: 位置: 使用:	Canon ✓ 選擇	LBP7110Cv 驅動程式…	v		
名稱: 位置: 使用:	Canon ✓ 選擇	LBP7110Cv 驅動程式…	v		
名稱: 位置: 使用:	Canon ✓ 選擇 自動	LBP7110Cv 驅動程式… 選擇 軟體…	v		
名稱: 位置: 使用:	Canon ✓ 選擇 自動 選擇	LBP7110Cv 驅動程式… 選擇 軟體…	v		

b) 輸入 7110 以搜尋「Canon LBP7100C/7110C」(type "7110", then choose "Canon LBP7100C/7110C")

$\bigcirc \bigcirc \bigcirc$	印表機軟體	
	Q 7110	8
Canon LBP7100C/7110C		
	取消	好

24. 加入完成 (Finish)

印表機 Canon LBP7110Cw ● 開置,最近使用的装置	Canon LBP7110Cw 丁開列印佇列… 選項與耗材… 位置: 種類: Canon LBP7100C/7110C 狀態: 開置
+ -	□ 在網路上共享此印表機 共享編好設定…
	預設印表機: 最近使用的印表機 🛟
	預設紙張大小: ▲4

-完--End-