LBP7110Cw以有線LAN連線連接印表機之驅動程式步驟 (以Win 10作示範) The Driver installation procedure for LBP7110Cw (Via LAN)(Win 10 as example)

注意: 安裝驅動程式前請勿接駁USB線,以免系統發生錯誤 ** Please don't plug the USB cable until the driver asked to do so**

開啟印表機

Turn on the printer

使用區域網路纜線將本機連接到路由器

Connect the machine to a router by using a LAN cable.

推入接頭,直至聽到喀嗒聲

Push the connector in until it clicks into place.



等待約2分鐘

Wait approximately 2 minutes 等待時,會自動設定 IP 位址 While you wait, the IP address is set automatically.

 到佳能網站<u>http://support-hk.canon-asia.com/</u>,選擇相關的印表機型號及下載 印表機的驅動程式

(Go to: <u>http://support-hk.canon-asia.com/</u>, select related printer model, then download the printer driver)

 下載的文件以自解壓縮檔檔案(.exe格式)保存在指定的文件夾中,打開文件解壓 縮。將在同一文件夾中創建新文件夾。新文件夾的名稱與解壓縮文件的名稱相同 (Open "LBP7100Cn_LBP7110Cw***.exe", a new folder will be created.)
 -如打開文件解壓縮時出現「使用者帳戶控制」選項,請按「是」(If "User Account Control" window pop-up. Choose "Yes")

💺 🗹 📜 후 Downloads					-	×
File Home Share View						~ 🕐
\leftarrow \rightarrow \checkmark \uparrow 🚺 \diamond This PC \diamond	Downloads >			νŪ	Search Downloads	Ą
📌 Quick access	Name	Date modified	Туре	Size		
🐉 Dropbox	LBP7100Cn_7110Cw_V2062_W32_uk_EN_3	27/10/2015 11:16	File folder			
la OneDrive	EBP/100Cn_/110Cw_V2062_W32_uk_EN_3	27/10/2015 11:09	Application	37,596 KB		
S This PC						
🔮 Network						
📢 Homegroup						
2 items 1 item selected						

3. 進入文件夾,「Driver」文件夾,然後開啓"Setup.exe"文件開始安裝設定 (Go into "Driver", then Double Click / Open "Setup.exe")

,				,			
📕 🛃 📕 🖛	Application Tools Driver					- 0	\times
File Home Share View	Manage						~ 🕐
\leftarrow \rightarrow \checkmark \uparrow \blacksquare \rightarrow This PC \rightarrow	Downloads > LBP7100Cn_7110Cw_V2062_W32_	_uk_EN_3 > Driver >		•	・ じSearch Drive		م
📌 Quick access	Name	Date modified	Туре	Size			
Drankay	Appendix	27/10/2015 11:16	File folder				
Se Diopbox	Driver	27/10/2015 11:16	File folder				
le OneDrive	MISC	27/10/2015 11:16	File folder				
This PC	T Readme	3/6/2013 9:00	HTML Application	79 KB			
a marc	Setup	19/4/2013 9:00	Application	2,704 KB			
🕩 Network	🔊 Setup	19/4/2013 9:00	Configuration setti	1 KB			
•4 Homegroup							
6 items 1 item selected 2.63 MB							100 E

4. 按「Yes」 (Click "Yes")

icense Agreement	
Please read the following license agreement completely and carefully. Click [Yes] to agree to the license agreement.	
CANON SOFTWARE LICENSE AGREEMENT	^
IMPORTANT!	
This is a legal agreement ("Agreement") between you and Canon Inc. ("Canon") and governir your use of Canon's software programs including the related manuals or any printed material thereof (the "Software") for certain Canon's copying machines, printers and multifunctional peripherals (the "Products").	ng
READ CAREFULLY AND UNDERSTAND ALL OF THE RIGHTS AND RESTRICTIONS DESCRIBED IN THIS AGREEMENT BEFORE INSTALLING THE SOFTWARE. BY CLICKIN THE BUTTON INDICATING YOUR ACCEPTANCE AS STATED BELOW OR INSTALLING THE SOFTWARE, YOU AGREE TO BE BOUND BY THE TERMS AND CONDITIONS OF THI AGREEMENT. IF YOU DO NOT AGREE TO THE FOLLOWING TERMS AND CONDITIONS OF THIS AGREEMENT, DO NOT USE THE SOFTWARE. NO REFUND WILL BE MADE BECAUSE THE SOFTWARE WAS PROVIDED TO YOU AT NO CHARGE.	IG [5
Do you agree to the terms in license agreement?	
< Back Yes No	

5. 選「Search for Network Printers to Install」, 按「Next」 (Select "Search for Network Printers to Install", then click "Next")

Printer Installation Select printer installation.		
Printer Installation	Manually Set Port to Install Search for Network Printers to Install	Detailed Settings
	O Install with USB Connection	
Installs printers connecte	d to the TCP/IP network.	
	< <u>B</u> ack	Next > Cancel

 從IPv4 Devices點選印表機,按「Add」新增印表機如下圖,按「Next」(Select Printer at IPv4 Devices Printer List, Press "Add" add printer, then click "Next")

Select the printers	to add, and then di	ck [Add].	
IPv4 Devices			Manual Search by IP Address
Printer List:			
Device Name	Product Name	IP Address	MAC Address
LBP7110Cw	LBP7110Cw	192.168.1.117	DCi
4			>
			Select All Search Again
Printer List for <u>D</u> rive	Add r Installation:		/e
Device Name	Product Name	IP Address	MAC Address
Set Printer Inform	mation		
		< <u>B</u> ack	Next > Cancel
Select Printers to Ins Select the printers	stall to add, and then clic	k [Add].	
Select Printers to Ins Select the printers	stall to add, and then clic	:k [Add].	Manual Search by IP Address
Select Printers to In: Select the printers IPv4 Devices Printer List:	stall to add, and then clic	dk [Add].	Manual Search by IP Address
Select Printers to Ins Select the printers IPv4 Devices Printer List: Device Name	stall to add, and then clic Product Name	lk [Add]. IP Address	Manual Search by IP Address MAC Address
Select Printers to Ins Select the printers IPv4 Devices Printer List: Device Name	stall to add, and then clic Product Name	IP Address	Manual Search by IP Address MAC Address
Select Printers to Ins Select the printers IPv4 Devices Printer List: Device Name	stall to add, and then clic Product Name	lk [Add]. IP Address	Manual Search by IP Address MAC Address
Select Printers to Ins Select the printers IPv4 Devices Printer List: Device Name	stall to add, and then clic Product Name	ck [Add]. IP Address	Manual Search by IP Address MAC Address
Select Printers to Ins Select the printers	stall to add, and then clic Product Name	ck [Add]. IP Address	Manual Search by IP Address MAC Address Select All Search Again
Select Printers to Ins Select the printers	stall to add, and then clic Product Name	ck [Add]. IP Address	Manual Search by IP Address MAC Address
Select Printers to Ins Select the printers	stall to add, and then clic Product Name	dk [Add]. IP Address	Manual Search by IP Address MAC Address
Select Printers to Ins Select the printers	stall to add, and then clic Product Name Add r Installation: Product Name	IP Address	Manual Search by IP Address MAC Address Select All Search Again e
Select Printers to Ins Select the printers IPv4 Devices Printer List: Device Name Cevice Name Device Name LBP7110Cw	stall to add, and then clic Product Name Add r Installation: Product Name LBP7110Cw	IP Address IP Address IP Address IP Address I92.168.1.117	Manual Search by IP Address MAC Address Select All Search Again e MAC Address DC
Select Printers to Ins Select the printers IPv4 Devices Printer List: Device Name Cevice Name LBP7110Cw	stall to add, and then clic Product Name Add r Installation: Product Name LBP7110Cw	IP Address IP Address IP Address IP Address 192.168.1.117	Manual Search by IP Address MAC Address Select All Search Again e MAC Address DC
Select Printers to Ins Select the printers	stall to add, and then clic Product Name Add r Installation: Product Name LBP7110Cw	dk [Add]. IP Address IP Address IP Address 192.168.1.117	Manual Search by IP Address MAC Address Select All Search Again e MAC Address DC
Select Printers to Ins Select the printers	stall to add, and then clic Product Name Add r Installation: Product Name LBP7110Cw	dk [Add]. IP Address ↓ ↑ Remov IP Address 192.168.1.117	Manual Search by IP Address MAC Address Select All Search Again e MAC Address DC

7. 按「Start」 (Click "Start")

The setup program will install the drivers with the following settings. Confirm the settings.

Printer List for Driver Installation:

Add =
Printer: LBP7110Cw
Driver : Canon LBP7100C/7110C
Port : CNMFNP_DC

Click [Start] to install.

< <u>B</u>ack

<u>S</u>tart

Cancel

8. 正在安裝,請等待 (Waiting for the installation progress)



9. 建議剔選「Restart My Computer Now」,按「Restart」重新開機 (We recommend choose "Restart My Computer Now", and then restart computer)



-完-

-End-